NM1

1" M1 LED Miniature Recessed Series

Source: 2W LED 100lm

Туре		
Project		
Catalog No.		
Notes		

PRODUCT DESCRIPTION

M1 miniature recessed series features quality and convenience with easy installation for indoor or outdoor applications. The IC rated M1 modules are excellent for niche lighting. Luminaires include four plastic downlight trims, four optics and 6" quick connect. Series is available in four color temperatures (2700K, 3000K, 3500K or 4000K) and requires a Class 2 12V DC driver

FEATURES

- No housing required
- Easy installation for remodel or new construction applications
- Field changeable optics (spot, narrow flood, flood & wide)
- Threaded LED module allows for field changeable trims
- Quick disconnect allows for extended lengths
- 100lm LED packages
- 2700K, 3000K, 3500K or 4000K @ 90+ CRI
- Triac or ELV dimming
- 5-year limited warranty
- **ENERGY STAR certified**

SPECIFICATION

Included with each luminaire: LED module includes four plastic trims (round and square) in black and white finishes. Also included are four optics for desired beam spread and output.

Construction: Threaded LED module allows for field changeable optics and trims.

Clearance: IC rated luminaires are rated for direct contact with insulation (not spray foam insulation). When LED module NM1 is installed in a cabinet type installation, minimum distance between luminaires is 6".

Driver: Class 2 power supply required, ordered separately. NM1-DVR drivers include a pre-wired junction box with quick connect to LED fixtures for ease of installation. NAPKED drivers require splitter cable or wire harness system (ordered separately).

Mounting: No housing is required, two tensions steel spring clips secure luminaire to surface. 1/4" minimum ceiling thickness.

Field Changeable Optics: Each luminaire includes four field changeable optics. 15° spot (frosted), 45° narrow flood (frosted - installed), 60° flood (frosted) and 60° flood (clear).

FI FCTRICAL

Input Voltage: 12V DC Lumens / Wattage: 100lm / 2W

Color Temperature: 2700K, 3000K, 3500K or 4000K

Beam Spread: 15° Spot, 45° Flood installed, Frosted 60° Wide Flood and Clear 60° Wide Flood (each luminaire includes all four optics)

Operating Temp: 0-40°C (Undercabinet installation) 0-25°C (Cabinet and IC installation)

Max. Run Length: Total combined runs cannot exceed 80' Dimming: Dimmable down to 10% with Triac or ELV dimmer Click Here or check complete dimmer list at

www.NoraLighting.com in the "Compatibility" page under "Resources" tab

NM1-RSS: Round Stainless Steel Trim NM1-SSS: Square Stainless Steel Trim NM1-RAEYELID: Round Scoop Trim

NM1-RSSD: Round Stainless Steel Indicator Trim

DRIVERS

NM1-DVR12: 12VDC 12W Non-Dimmable Hardwire Driver NAPKED-5040HW: 12VDC 35W IC Dimmable Hardwire Driver NAPKED-5060HW: 12VDC 60W Dimmable Hardwire Driver

ACCESSORIES

NM1-EXT: Quick Connect Linkable Extension Cables (available in 6", 12", 18", 48", 72" and 240") NM1-TM6: Splitter Cable (1 input - 6 output) NM1-WH6: Wire Harness System (1 input - 6 output) NM1-F: New Construction Frame-In

LABELS AND LISTINGS

cETLus Listed for Wet Locations, cabinet and type IC

cETLus Listed for Damp Locations, under-cabinet and type IC (NM1-DVR12)

cETLus Listed for Damp Locations, cabinet and type IC (NAPKED-5040HW)

- cETLus Listed for Damp Locations and cabinet (NAPKED-5060HW)
- **ENERGY STAR certified**
- 5-Year Limited Warranty
- FCC compliant
- Can be used to comply with 2019 Title 24 part 6 High Efficacy LED light source requirements















PRODUCT IMAGES AND DIMENSIONS



1" M1 LED Miniature Recessed Series (includes two black & two white plastic trims)





NM1-RSS

* Requires NM1-170 *

NM1-SSS

1" Round Stainless Steel Trim 1" Square Stainless Steel Trim Requires NM1-170 *





NM1-RSSD

1" Round Stainless Steel Indicator Trim * Requires NM1-170 *

NM1-RAEYELID

1" Round Scoop Trim * Requires NM1-170 *







Cut out: 1-3/8"

1" M1 LED Miniature Recessed

M1 LED Module Color Temperature / CRI Trims / Finishes NM1-170 = 1" LED Module **27X** = 2700K / 90 CRI 2PBW = (2) Black & (2) White Plastic Trims 30X = 3000K / 90 CRI 35X = 3500K / 90 CRI **40X** = 4000K / 90 CRI

1" M1 Trims - Requires NM1-170 LED Module

M1 Trims Finish NM1-RSS = 1" Round M1 Stainless Steel Trim B = Black NM1-RAEYELID = 1" Round M1 Scoop Trim BN = Brushed Nickel NM1-RSSD = 1" Round M1 Stainless Steel Indicator Trim W = White NM1-SSS = 1" Square M1 Stainless Steel Trim

Optional Accessories

Description

NM1-DVR12 = 12VDC 12W Non-Dimmable Hardwire Driver NAPKED-5040HW = 12VDC 35W Dimmable Hardwire Driver NAPKED-5060HW = 12VDC 60W Dimmable Hardwire Driver NM1-EXT6 = 6" Quick Connect Extension Cable NM1-EXT12 = 12" Quick Connect Extension Cable

NM1-EXT18 = 18" Quick Connect Extension Cable NM1-EXT48 = 48" Quick Connect Extension Cable

NM1-EXT72 = 72" Quick Connect Extension Cable NM1-EXT240 = 240" Quick Connect Extension Cable

NM1-TM6 = Splitter Cable (1 input - 6 output) NM1-WH6 = Wire Harness System (1 input - 6 output)

NM1-F = New Construction Frame-In

Example: NM1-17030X2PBW / NM1-DVR12 = 1" M1 LED Module and (4) Plastic Trims / 12VDC 12W Non-Dimmable Hardwire Driver



NM₁

1" M1 LED Miniature Recessed Accessories


Type
Project
Catalog No.
Notes



12VDC Non-Dimmable Hardwire Driver

NM1-DVR12 12W

Input Voltage: 120V Output Voltage: 12V DC Maximum Load: 10W Dimming: Non-Dimmable Includes: Quick connect cable to NM1 module





Quick Connect Extension Linkable Cables

 NM1-EXT6
 6" Cable

 NM1-EXT12
 12" Cable

 NM1-EXT18
 18" Cable

 NM1-EXT48
 48" Cable

 NM1-EXT240
 240" Cable

Use to extend the length between luminaire and driver / splitter / wire harness. Can be connected together to create custom lengths. Can be used as power feed for NAPKED LED drivers. Maximum length between luminaire and driver is 80'.



Splitter Cable (1 input - 6 output)

NM1-TM6

Use to connect up to (6) NM1 LED modules to an LED driver. Maximum length between luminaire and driver is 80°. Includes power feed for NAPKED LED drivers.

Input wire length: 4-3/4" Output wire lengths: 5-1/4" each



12VDC Dimmable Hardwire Driver


NAPKED-5040HW 35W (IC)

Input Voltage: 120V Output Voltage: 12V DC Maximum Load: 28W

Compartment Clearance: Minimum compartment size is 11-1/2" x 3-1/2" x 11-1/2"

Dimming: Triac or ELV

Requires: Splitter cable or or wire harness system



12VDC Dimmable Hardwire Driver

NAPKED-5060HW

Input Voltage: 120V Output Voltage: 12V DC

Maximum Load: 48W

Compartment Clearance: Minimum compartment

60W (Non-IC)

size is 11-1/2" x 3-1/2" x 11-1/2"

Dimming: Triac or ELV

Requires: Splitter cable or or wire harness system



Wire Harness System

NM1-WH6


Use to connect up to (6) NM1 LED modules to an LED driver on an evenly spaced wire. Each 6" dropped is spaced 32-1/2" on center. Maximum length between luminaire and driver is 80'. Includes power feed for NAPKED LED drivers. Spacing between luminaires: 32-1/2" Output wire length: 6" each



New Construction Frame-In

NM1-F

For new construction pre-wiring and easier layout planning. Includes wire clip that holds low voltage connector close to cut-out during rough-in installations.



PHOTOMETRICS

1" M1 LED Miniature Recessed Series


Type
Project
Catalog No.
Notes

Test Information

Test Number: ALD-PG190715009 Part Number: NM1-17027X2PBW Beam Spread: Narrow Flood

Lumens: 100lm Wattage: 2.1W Efficacy: 98lpw

CCT / CRI: 2700K / 90 CRI Spacing Criteria (0°-180): 0.68 Spacing Criteria (90°-270): 0.56



Illuminance at a Distance

marimanoo at a biotanoo				
Distance from Luminaire	FC at Nadir	Beam Diameter		
2'	65.5fc	1'-2"		
4'	16.4fc	2'-6"		
6'	7.3fc	3'-8"		
8'	4.1fc	4'-11"		
10'	2.6fc	6'-2"		

Zonal Lumen Summary

Zone	Lumens	% Luminaire		
0-30	89	91		
0-40	96	98.1		
0-60	98	100		
0-90	98	100		
90-180	0	0		
0-180	98	100		

Candela Table

Carideia Fable		
Vertical Angles	Candela	
0	262	
5	259	
15	193	
25	66	
35	15	
45	3	